

Complete Your Flat Panel TV With Powerful Digital Home Theater Surround

Flat panel TVs create stunning pictures. Their sound should be, stunning too. Which is why we've created the SurroundBar® 6000 Instant Home Theater™. Our latest SurroundBar is the sleekest, leanest, self-powered single-speaker surround solution yet. The SurroundBar 6000 blends almost seamlessly with the new generation of TVs, while the wireless subwoofer tucks away anywhere you want it to. But the real beauty of the SurroundBar 6000 becomes evident the moment you turn it on. That's when your flat panel comes alive with the astonishing performance of Polk's 3D Audio. You'll never look at your flat panel TV the same way again.



Features

- **Less Than 2" Deep**, the SurroundBar's sleek design blends seamlessly with today's contemporary TV designs.
- **3D Audio**—a combination of Polk Audio's proprietary SDA® Surround and Polk Digital Logic™ technologies—creates a rich, enveloping listening experience far beyond what any built-in TV speakers can produce.
- **Dolby® Digital Decoding** for the kind of full, clear sound you want from all your digital sources.
- **ENERGY STAR® Certified**.
- **Polk Audio's Signature Sound**, warm and full with clarity and detail, turns games, movies and TV into a more exciting viewing experience.
- **Powerful Wireless Subwoofer** creates deep bass impact and can be placed anywhere in the room within 50' of the SurroundBar 6000.
- **SmartBar™ Programming** enables the SurroundBar 6000 to easily learn volume up/down and mute from your existing TV remote control. You'll use only one remote for the SurroundBar and your TV.
- **6' Optical Cable** included for the quickest, easiest hookup from your TV to the SurroundBar 6000.
- **Built-In Keyhole Slots** for wall-mounting ensure a wide range of placement options.
- **Simple, Touch-Sensitive Keypad Controls** on the bar include programming function for your existing remote control.
- **Included Remote Control** has simple, minimalist layout for: on/off, bar volume, subwoofer volume, mute and source selection.



SurroundBar 6000 Inputs:

- ❶ **Audio Inputs (Source 1, 2 or 3)**—Where you connect your TV (or other source) to the SurroundBar 6000. Use the 6' optical cable (Source 1) provided or 1/8" analog cable (Source 2 or 3) provided.

Specifications

SurroundBar 6000 IHT

| | | |
|---|------------------|--|
| Driver Complement | SurroundBar 6000 | Four 2 3/4" drivers (7 cm) |
| | Subwoofer | One 7" Woofer (17.78 cm) |
| System Power | | 280 Watts (160 W Bar & 120 W Sub) |
| Overall System Frequency Response (-3dB Limits) | | 40 Hz - 20 kHz (50 Hz - 16 kHz) |
| Dimensions | SurroundBar 6000 | 3 3/4" H x 35" W x 1 31/32" D (9.53 cm x 89 cm x 5 cm) |
| | Subwoofer | 11" H x 10 1/4" W x 12" D (27.94 cm x 26.04 cm x 30.48 cm) |
| Warranty | | 3 years speaker, 1 year electronics |

Specifications, dimensions and features subject to change without notice. For more information call us at 1-800-377-7655 (USA and Canada). Outside of North America call +1 (410) 358-3600.