



A New Dimension In Sound With Stunning Simplicity

Legendary Polk Audio® sound combines with Polk Digital Logic™ to make watching TV and movies not only more exciting, but also incredibly easy. Using a single SurroundBar® loudspeaker and a wireless subwoofer, the SurroundBar SDA® Instant Home Theater produces a generous soundstage and rich, full sound. To get started connect the SurroundBar SDA to your TV and plug in its power cord. Then plug in the wireless subwoofer. Polk Audio's patented SDA technology and Polk Digital Logic does the rest, bringing spectacular performance and convenience to all of us whose budget is limited but whose desire for great sound isn't.

Features

- **Easy To Set Up.** Instant home theater in minutes.
- **A Complete Home Theater Experience** from a single speaker and an unobtrusive wireless subwoofer.
- **No Rear Speakers, No Rear Wires.**
- **Polk® Digital Logic** guarantees the highest level of performance with no complicated setup and calibration.
- **Four 2 1/2" Bass Midrange Drivers** for superb midrange detail and definition. Two 2 1/2" treated composite fiber stereo bass midrange drivers and two 2 1/2" treated composite fiber dimensional bass midrange drivers.
- **Dynamic Balance® Drivers** produce flat frequency response, sharp detail. The sound is always clean, clear and effortless.
- **5' Audio Cable** for the absolute easiest hookup from your TV to the SurroundBar SDA.
- **Easy To Install On A Wall**, thanks to built-in key hole slots.
- **Cradle Mounts** give you more on-shelf positioning options.
- **Designed To Sit On A Flat Surface** without using cradles.
- **Black Cabinet Matches TVs.**

Easy Hookups And Simple Controls

SurroundBar SDA

LED—A light shines green, orange or red to indicate operating status.

Power—Turns on the SurroundBar SDA or puts it in standby mode.

Mute—Mutes the sound coming from the SurroundBar SDA and wireless subwoofer.

Volume—Up and down adjusts the volume on the SurroundBar SDA and wireless subwoofer.

Remote—Puts the SurroundBar SDA into learning mode so you can program it to respond to commands from your remote control.

Channel ID Switch—Selects the channel for the wireless subwoofer signal.

Gain Level Switch—Adjusts the input sensitivity of SurroundBar SDA.

Audio Inputs—Where you connect your TV to the SurroundBar SDA.

Wireless Subwoofer

Downward Firing Powered Subwoofer—A compact vented enclosure with an 6 1/2" long-throw Dynamic Balance poly composite driver for big, musical bass.

Channel ID Switch—Selects the channel for the wireless subwoofer signal.

Volume—Adjusts the volume of the subwoofer to balance with the SurroundBar SDA.

Status Light—Shines red when the subwoofer is active and green when it's in standby mode.

Power On/Off Switch—Turns the wireless subwoofer on and off.



SDA Surround Technology

Specifications	System	SurroundBar SDA	Wireless Subwoofer
System Power	130 Watts	(35 Watts x2)	(60 Watts x1)
Overall System Frequency Response	40Hz - 22kHz		
Total Peak System Power	260 Watts	(70 Watts x2)	(120 Watts x1)
Dimensions		4" H x 31 3/4" W x 4 5/8" D (101mm x 807mm x 118mm)	10" H x 10 1/4" W x 10 1/4" D (254mm x 261mm x 254mm)
Dimensions With Cradle		5 3/8" H x 31 3/4" W x 4 5/8" D (137cm x 807mm x 118mm)	
Weight		8.7 lbs (3.9kg)	9.1 lbs (4.1kg)
Speaker Warranty	1 year electronics, 5 years speakers		
MSRP US\$	\$499		

Specifications, dimensions and features subject to change without notice. For more information call us at 1-800-377-7655 (USA and Canada). Outside of North America call +1 (410) 358-3600.